



- SEE CATALOG PAGE FOR MORE INFO.
- SQUARE IS DESIGNED FOR UNDERCABINET OR ANY APPLICATION WHERE MINIMAL PROFILE IS REQUIRED OR DESIRED.
- LAMP LEAD CABLE OR CONDUIT NORMALLY EXTENDS FROM BACK RIGHT OF LUMINAIRE.
- STANDARD UNDERCABINET CONFIGURATION USES 1/2" TUBE BETWEEN LUMINAIRE AND BALLAST BOX.
- REMOTE UNIVERSAL BALLAST W/ PLUG OR HARDWIRE PROVISION FROM ONE END.

ORDERING/SPECIFICATION GUIDE--SQUARE

COMPLETE NUMBER = AAAABBCCDDEEFGHIJKLM

AAAA	BB	CC	DD	EE	F	G	H	I	J	K	L	M
<u>SQUARE</u>	<u>MOUNTING</u>	<u>LAMP TYPE</u>	<u># OF LAMPS</u>	<u>LAMP WATTAGE</u>	<u>LAMP COLOR</u>	<u>EXTRUSION COLOR</u>	<u>SHIELDING</u>	<u>ENDCAP TYPE</u>	<u>WIRING</u>	<u>DIMMING</u>	<u>EMERGENCY</u>	<u>OTHER</u>
1400=	01=Custom 77=Cubes Gray 78=Cubes White	02=T5	01=1 02=2	08=14W 08=21W 09=24W 10=28W 11=35W 13=39W 18=54W	2=830 3=835 4=841 5=880 6=885 7=Red 8=Green 9=Blue	1=Clear Anodized 2=White 3=Custom	2=Acrylic Frosted Lens	1=Custom 4=White Plastic 6=Gray Plastic	1=Portable w/ Plug 3=Hardwire w/Conduit	1=Non-Dimming 2=Dim 10% 120V 3=Dim 1% 120V 4=Dim 10% 277V 5=Dim 1% 277V 6=Custom Dim 120V 7=Custom Dim 277V 8=Dim 0-10V 120V 9=Dim 0-10V 277V	1=Non-Emergency 0=Standard	